

PCMark 10

4 709

Essentials

9 315

Apps Start-up score

12 274

Video Conferencing Score

7 649

Web Browsing Score

8 610

Productivity

6 178

Spreadsheets Score

5 606

Writing Score

6 810

Digital Content Creation

4 927

Photo Editing Score

8 110

Rendering and Visualization Score

3 052

Video Editing Score

4 833

Validation

ERROR

Run information

Result name

DESKTOP-9T4QTGU_2022-09-23 02:22:22.0

Result details

SystemInfo Version

5.51.1126

UI Version

2.1.2556 s64

Test Version

1.0

Date

September 23 2022

Duration

24 m 47 s

Id

677bcc2c-bfa4-471b-aa2c-fa008148584c

Test settings

Default settings used

Yes

Additional output

Video Conferencing

Video Encoder, Intel® Quick Sync Video H.264 Encoder MFT

Video Conferencing

OpenCL, Intel(R) Iris(R) Xe Graphics

Spreadsheets

OpenCL, CPU

Photo Editing

OpenCL, Intel(R) Iris(R) Xe Graphics

Video Editing

OpenCL, Intel(R) Iris(R) Xe Graphics

System details

General

Operating System	Windows 10 Home Single Language 64-bit 10.0.19043
Motherboard	ASUSTeK COMPUTER INC. UX5401EA
Memory	16076 MB DDR4
BIOS	American Megatrends International, LLC. UX5401EA.302
System Drive Model	
Resolution	1440 x 900 px
Power plan	Balanced

Processor

CPU	11th Gen Intel(R) Core(TM) i5-1135G7 @ 2.40GHz
Clock Frequency	2400 MHz
Max Frequency	4337 MHz
Processors	1
Cores	4 (8)
Package	Socket 1449 FCBGA

Graphic adapters

GPU	Intel(R) Iris(R) Xe Graphics
Manufacturer	Intel
Dedicated Video Memory	
Total Available Graphics Memory	8038 MB
Core Clock	1300 MHz
Boost Clock	1300 MHz
Memory Clock	1600 MHz
Driver Version	27.20.100.9664
Display 1	\\.\DISPLAY1 (2880 x 1800, 200% DPI scaling)

Storage devices

Drive 0	476 GB
Drive model	NVMe SAMSUNG MZVL2512HCJQ-00B00
Drive type	SSD
External drive	No (SCSI)
Partition 0	100 MB
Partition 1	C: (NTFS) 475 GB (380 GB free)
Partition 2	508 MB
Partition 3	1.0 GB
Partition 4	200 MB

Batteries

Battery	ASUS Battery
Manufacturer	ASUSTeK
Type	Unknown
Cycle count	1
Designed capacity	63004 mWh
Full charged capacity	63699 mWh
Wear level	-1.1%

Hardware monitoring

